


5 IN 1 Slim Panel LED Recessed Downlight




EASY INSTALLATION



IC Rated Junction Box

1-3




- 1 Install the drywall directly over the rough-in paper.
NOTE: It is suggested to use your own method in locating the center of the aperture hole.
- 2 Select your desired method of cutting either using a hand saw or hole saw to cut an opening in the ceiling by using the provided template.
- 3 After selecting the desired method of cutting, cut out a 6.33" diameter hole in the mounting surface.

CAUTION:


Do NOT cut a hole that exceeds or that is larger than the paper opening.

4-5



- 4 Make sure all POWER IS TURNED OFF at the electrical source to the location in which you are mounting the luminaire.
- 5 Remove the cover of the provided J-BOX and insert wire nuts to make connections with power supply. Insert splices in J-BOX before concealing the cover.

8-9



- 8 Place the J-BOX through the cut-out hole and mount according to your local electrical code compliance.
- 9 Rotate and hold both spring clips upward to allow passage through the cut-out in the ceiling.
Continue to press the light module through the cut-out hole until it is securely fixed and flushed with the ceiling.

6




- 6 Connect the J-BOX to the light module.
- 7 Turn on the power and slide the CCT Selection Switch to test the light.

BEFORE INSTALLATION:

On the back of the J-BOX, slide the CCT Selection Switch and choose from five available color temperatures: 2,700K; 3,000K; 3,500K; 4,000K; and 5,000K.

- Test results from each CCT Selection to determine which brightness level suits your room best.
- The light will use the preferred setting whenever you turn on the switch.
- Turn off the light switch and continue with the installation.

7



WARNING

- RISK OF FIRE OR ELECTRIC SHOCK
CONSULT A QUALIFIED ELECTRICIAN TO ENSURE CORRECT BRANCH CIRCUIT CONDUCTOR.
- RISK OF FIRE MIN 90°C SUPPLY CONDUCTORS.
- DO NOT make or alter any open holes in an enclosure of wiring or electrical components during kit installation.
- To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects.

CAUTION

- Edges may be sharp. Please wear gloves while handling.
- Product designed for dimming with many 120V TRIAC/ELV phase cut control dimmers.
- Product can be installed directly into a ceiling without requiring separate J-box or recessed housing.
- Connect fixture to a 120V 60Hz power source, any other connection voids the warranty.

SPECIFICATIONS

Voltage	120V
Wattage	12W
Suitable for Locations Ingress	Damp
Housing	Aluminum
Weight	0.66lbs
Warranty	5 years