



Wireless Headphone KH186



User Manual

SUPPORT EMAIL: service@lincisoonic.com

Contents		
1.Product Overview-----	2	
2.Basic Operation-----	3	
3.Bluetooth Pairing and Connection-----	4	
4.Connection with Two Devices-----	5	
5.LED Indicator-----	6	
6.Charging-----	6	
7.Product Specification-----	7	
8.Attentions and Q & A-----	8	



Scan to get

- Lifetime Extended Warranty.
- Technical support if you have any usage problems.

Customer service email: service@lincisoonic.com

1.Product Overview



Packing list:

- A. Wireless Headset KH186 x 1
- B. Micro USB charging cable x 1
- C. User manual x 1





2. Basic Operation

Button	Function	Operation Instruction
	Power On	In the off status, press and hold MFB for 5-7 seconds to power on. You will hear the voice prompt: Power on.
	Power Off	In the on status, press and hold MFB for 5 seconds to power off. You will hear the voice prompt: Power off.
Enter Pairing Mode		In the off status, press and hold MFB for 5-7 seconds to power on. KH186 will enter pairing mode automatically in the unconnected standby status, double click MFB to enter pairing mode.
		After the Bluetooth is disconnected, KH186 will enter pairing mode automatically.
MFB	Play / Pause	Single click MFB to play / pause when playing music.
	Redial a Call	Double click MFB to redial the last call.
	Voice Assistant	Press and hold MFB for 1 second to wake up the voice assistant.
	Audio Switch	During a call, press and hold MFB for 1 second to switch the audio between phone and Bluetooth headset.
	Answer a call	When a call comes in, single click MFB. (Please note, the MFB can only answer/hang up mobile phone calls)
	Hang up a call	During a call, single click MFB.
	Reject a call	When a call comes in, press and hold MFB for 1 second.
Second Call		When a call comes in during a call, single click the MFB to answer the new call and hang up the current call. Double click the MFB to answer the new call and place the current call on hold. Double-click the MFB again to switch between the current call and the held call.
Clear Pairing Record		In standby status, press and hold volume + and MFB at the same time for 5 seconds to clear the pairing record.


3.Bluetooth Pairing and Connection

A. In the off status, press and hold MFB for 5-7 seconds to enter pairing mode, the LED flashes blue and red alternately.

B. Search and click to connect KH186 on the Bluetooth list of your device, the LED flashes blue when connected.


C. Now you can use the Bluetooth headset to adjust the volume, track music, answer/end/reject the call, wake up the voice assistant and do other operations.

1



Enter Pairing Mode. Press and hold MFB for 5-7 seconds, the LED flashes blue and red alternately.

2



Search and Connect. Turn on Bluetooth of the cell phone, search "KH186" and click to connect.

4. Connection with Two Devices



A. In the off state, press and hold MFB for 5-7 seconds to power on and enter pairing status. Turn on the bluetooth of the first device, search "KH186" and click to connect.

B. After the connection is successful, turn off the Bluetooth on the first device, KH186 will enter pairing mode automatically. Turn on the Bluetooth on the second device, search "KH186" and click to connect.

C. Turn on the Bluetooth on the first device, click "KH186" and connect the Bluetooth headset.



*When connected to 2 devices, audio can only be played from one device. If you want to play music from another device, please turn off the music on the previous device. The same is true when making a call.

5. LED Indicator <table border="1"> <thead> <tr> <th>Mode</th><th>LED Indicator</th></tr> </thead> <tbody> <tr> <td>Power on</td><td>Blue LED flashes 3 times</td></tr> <tr> <td>Power off</td><td>Red LED is on for 1 second</td></tr> <tr> <td>Pairing mode</td><td>Red and blue LEDs flash alternately</td></tr> <tr> <td>Connected standby mode</td><td>Blue LED flashes once every 10 seconds</td></tr> <tr> <td>Playing Music</td><td>Blue LED flashes twice every 10 seconds</td></tr> <tr> <td>Calling</td><td>Blue LED flashes twice every 10 seconds</td></tr> <tr> <td>Clear pairing record</td><td>Red and blue LEDs flash once at the same time</td></tr> <tr> <td>Charging</td><td>Solid Red LED</td></tr> <tr> <td>Full charged</td><td>Solid Blue LED</td></tr> <tr> <td>Low battery</td><td>Red LED flashes</td></tr> </tbody> </table> 6. Charging Please charge the KH186 when the red LED flashes (battery low). Charging time is about 2 hours. Solid Red LED turns off and Blue LED turns on when full charged. Please charge the KH186 through the Micro USB charging cable.	Mode	LED Indicator	Power on	Blue LED flashes 3 times	Power off	Red LED is on for 1 second	Pairing mode	Red and blue LEDs flash alternately	Connected standby mode	Blue LED flashes once every 10 seconds	Playing Music	Blue LED flashes twice every 10 seconds	Calling	Blue LED flashes twice every 10 seconds	Clear pairing record	Red and blue LEDs flash once at the same time	Charging	Solid Red LED	Full charged	Solid Blue LED	Low battery	Red LED flashes	  Charging with Charger *Note: Please charge the KH186 at least once every 2 months when not in use. 7. Product Specification <table border="1"> <tbody> <tr> <td>Bluetooth Version</td><td>Bluetooth V5.3</td></tr> <tr> <td>Bluetooth Chipset</td><td>BT8926B</td></tr> <tr> <td>Operation Range</td><td>30 ft (Barrier-free place)</td></tr> <tr> <td>Bluetooth Protocols</td><td>HSP HFP A2DP AVRCP</td></tr> <tr> <td>CODEC</td><td>SBC/AAC</td></tr> <tr> <td>Charging Time</td><td>About 2 hours</td></tr> <tr> <td>Talking Time</td><td>About 35 hours(70% volume)</td></tr> <tr> <td>Working Time</td><td>About 60 hours(70% volume)</td></tr> <tr> <td>Headset Net Weight</td><td>About 141g</td></tr> <tr> <td>Headset Dimension</td><td>200*110*75mm</td></tr> </tbody> </table> *The actual use time will vary depending on the environment and usage conditions.	Bluetooth Version	Bluetooth V5.3	Bluetooth Chipset	BT8926B	Operation Range	30 ft (Barrier-free place)	Bluetooth Protocols	HSP HFP A2DP AVRCP	CODEC	SBC/AAC	Charging Time	About 2 hours	Talking Time	About 35 hours(70% volume)	Working Time	About 60 hours(70% volume)	Headset Net Weight	About 141g	Headset Dimension	200*110*75mm	9. Attentions and Q & A A. How to reconnect and what to do if reconnection fails? When KH186 is connected to your cell phone successfully once, it will reconnect to the paired device when powered on. If failed, please connect it manually. Press and hold MFB for 5-7 seconds to enter into pairing mode, then click and connect KH186 on your cell phone. B. How to delete paired records? In standby status, press and hold volume + and MFB at the same time for 5 seconds to clear the pairing record. After that, the KH186 will not automatically connect to previous devices. C. What's the password for pairing? Some connection devices require password for pairing, please try 0000 or 8888 or 1111 or 1234. D.How to activate Siri? Press and hold MFB for 1 second to wake up the voice assistant. E. How to do if there is a connection issue? Please try charging reset: plug in charging cable to charging, this will reset the headset to power off. Then remove the charging cable, press and hold the MFB to power on. If you still cannot use it normally, please	contact customer service or manufacturer for technical support. F. Power off automatically? The KH186 will automatically shut down if there is no connection for more than 10 minutes or if the battery is low. G: I cannot answer or reject calls on computer? The MFB can only answer/hang up mobile phone calls, when connecting to computer or landline, the MFB is unavailable. H: How can I contact the seller if I have any other problem? If you have any problems, please feel free to email us: SUPPORT EMAIL: service@lincisoonic.com	FCC Warning This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: - Reorient or relocate the receiving antenna. - Increase the separation between the equipment and receiver. - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. - Consult the dealer or an experienced radio/TV technician for help.	The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.
Mode	LED Indicator																																														
Power on	Blue LED flashes 3 times																																														
Power off	Red LED is on for 1 second																																														
Pairing mode	Red and blue LEDs flash alternately																																														
Connected standby mode	Blue LED flashes once every 10 seconds																																														
Playing Music	Blue LED flashes twice every 10 seconds																																														
Calling	Blue LED flashes twice every 10 seconds																																														
Clear pairing record	Red and blue LEDs flash once at the same time																																														
Charging	Solid Red LED																																														
Full charged	Solid Blue LED																																														
Low battery	Red LED flashes																																														
Bluetooth Version	Bluetooth V5.3																																														
Bluetooth Chipset	BT8926B																																														
Operation Range	30 ft (Barrier-free place)																																														
Bluetooth Protocols	HSP HFP A2DP AVRCP																																														
CODEC	SBC/AAC																																														
Charging Time	About 2 hours																																														
Talking Time	About 35 hours(70% volume)																																														
Working Time	About 60 hours(70% volume)																																														
Headset Net Weight	About 141g																																														
Headset Dimension	200*110*75mm																																														
06	07	08		09	FCC ID: WSG-KH186 Made in China   																																										

SIZE: 80X120MM ,
128克双铜纸双面单黑印刷 过油 折叠 (手风琴式)