



ZJE0066 8-Port Shared Power Bank Cabinet

Specification Sheet

1. Product Overview

Product Name: 8-Port Shared Power Bank Cabinet

Model: ZJE0066

Application: Shared power bank rental service

Scenarios: Shopping malls, airports, stations, restaurants, hotels, public places

2. Physical & Appearance

Dimensions: 240mm × 190mm × 280mm

Material: ABS+PC, Fireproof V0

Color: Customizable

Display: 8-inch screen with acrylic cover

3. Structure & Charging

Slots: 8

Compatible power banks: ZJE0075 / 75A / 75B, ZJE0067A / 67B

Per-slot output: 5V 2A

Charging mode: 2 units charged simultaneously

4. Electrical Parameters

Input: AC 100–240V, 50/60Hz

Single output: DC 5V 2A

Total power: 36W

Power adapter: Built-in

5. Network & Communication

Module: China Mobile ML307A

Network: 4G

Protocols: TCP / MQTT

Support: Remote monitoring & management

6. Software & Payment

OS: Embedded system

Payment: WeChat Pay, Alipay

Functions: Data statistics, fault alarm, remote upgrade

7. Safety Features

Fireproof: Complies with national standards

Anti-theft: Anti-pry design

Protection: Over-voltage, over-current, short-circuit

Data: Encrypted storage

8. Environment

Operating temp: -10°C ~ 50°C

Storage temp: -20°C ~ 60°C

Humidity: 10% ~ 90% non-condensing

9. Installation & Maintenance

Install: Wall-mounted / Vertical

Mounting bracket: Optional (sold separately)

Maintenance: Recommended monthly

10. Packaging

Package size: 280mm × 240mm × 350mm

Package weight: 2.4kg (without power banks)

Transport: Land / Sea / Air

11. Service

Warranty: 1 year

Support: 7×24 online

Repair: Factory repair service

Accessory: Power cable

Manufacturer: Shenzhen Zhongju Dianneng Technology Co., Ltd. Address: 3rd Floor, No.24 Tongyu Road, Heping Street, Bao'an District, Shenzhen Tel: 186 8212 9528

FCC Warning

15.19 Labeling requirements.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

15.21 Information to user.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

15.105 Information to the user.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one

or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC RF Radiation Exposure Statement:

1. This Transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.
2. This equipment complies with RF radiation exposure limits set forth for an uncontrolled environment.
3. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.