POWER BUTTON LED INDICATORS	POWER SOURCE STATUS	USB BUTTON LED (LEFT)	AC BUTTON LED (RIGHT)	ACTION
AC POWER ON	READY TO POWER	N/A	SOLID GREEN	–
USB POWER ON	READY TO POWER	SOLID GREEN	N/A	–
AC LOW BATTERY ALERT	SHUTDOWN TIMER STARTED	N/A	FLASHING GREEN	CHARGE BATTERY
USB LOW BATTERY ALERT	SHUTDOWN TIMER STARTED	FLASHING GREEN	N/A	CHARGE BATTERY
AC OVERLOAD	MAX OUT WATTAGE	N/A	FLASHING RED	REDUCE LOAD, PRESS AC POWER BUTTON TO MANUALLY RESET THE UNIT
HIGH TEMPERATURE ALERT	INVERTER OVERHEATING	FLASHING YELLOW	FLASHING YELLOW	REDUCE LOAD, ALLOW UNIT TO COOL, THEN MANUALLY PRESS USB POWER BUTTON OR AC POWER BUTTON RESET

HIBERNATION MODE INSTRUCTIONS

HIBERNATION MODE [AUTOMATIC SHUTDOWN TIMER]

Hibernation mode helps conserve your battery by automatically turning off the power source when no significant power draw is detected for 3 hours. By default, Hibernation Mode is enabled, but users can turn it on or off with a simple button combination:

Turn Hibernation ON:

Hold Task Light Button and USB Power Button for 5 seconds.
USB power button will flash green 3 times.



Turn Hibernation OFF:

Hold Task Light Button and AC Power Button for 5 seconds.
AC power button will flash red 3 times.

