

455MM

200MM

正面

反面

SMART SWITCH USER MANUAL

03 Specification

Input Power:	100-120V AC 60Hz
Control:	Relay
Communication:	WiFi 802.11 b/g/n 2.4GHz
Max Current:	8A
Standby Power:	<0.5W
Button Life:	500K times
Dimension:	105*45*42.5 mm

04 Contents Supplied

Switch, Panel, Wire Caps, Screws

01 Product Outline

Cover Panel, ON/OFF, LED Indicator

02 Indicator Light Status

Light Color	Light Status	Switch Status	Remarks
ON	Power ON(Default)	Support Self-definition on APP	
OFF	Power OFF(Default)		
Green	Blink Quickly (0.5s)	Ready for default configuration mode	
	Blink Slowly (1s)	Ready for AP (Access Point) configuration mode	

05 Safety Information

WARNING: RISK OF ELECTRIC SHOCK

Electricity can cause personal injury and property damage if handled improperly. If you are not sure about any part of these instructions, please seek professional assistance from a qualified electrician. Ensure all work meets applicable local and national codes.

Tools you'll need

Phillips-head screwdriver, Flat-head screwdriver, Wire caps, Pliers, Voltage tester

06 Installation

30min Approximately 30 minutes to install and setup the switch

STEP 1 Turn Off Power

Locate your circuit breaker panel and turn off the power to each switch you are replacing.

STEP 2 Remove the switch and pull it away from the wall.

STEP 3 Verify Power is Off

We recommend you to remove the fuse/cap from the old switch and use an electrical tester to test all wires connected to the switch to ensure there is no voltage in the circuit.

STEP 4 Pull Out Old Switch

STEP 5 Identify the Old Switch

Single Pole Switch

STEP 6 Identify Line/Load Wire

Note: The color of your wire may be different from the color shown on the manual.

STEP 7 Test NEUTRAL and GROUND Wires

Make sure there is no power on the neutral wires from neighboring circuit. If necessary, shut off additional circuits until no voltage is found.

STEP 8 Take Pictures of the Wiring

Loosen the screw terminals and remove the old switch.

STEP 9 Wire the Smart Switch

Connection Diagram

Neutral (White), Line / Hot (black), Load (red), Ground (Green)

STEP 10 Mount the switch

STEP 11 Turn on the power

IMPORTANT

This product needs to charge the supercapacitor at the first time power-on. The charging time will take about 5-7 minutes. It will be slightly different depending on the load power and type.

Charge time 7 mins

Flicker due charging

The light may turn on or flicker during the charging process, this is normal situation, and the light will automatically go off after the charge is completed, the switch needs about 1 more minute to initialize, and then it will enter the normal working state.

07 Add Devices

STEP 1 Download Smart Life APP

STEP 2 Register And Login

STEP 3 Add the Switch to APP

Preparation: Ensure the switch has connected with electricity, ensure your phone has connected to Wifi router and is able to connect to the internet.

Note: The switch supports 2.4G Wi-Fi network only

After the user login, tap the "+" icon on the top right corner to add device; select the "switch" menu and choose the switch device icon.

STEP 3.1 Quick Configuration Mode

Press and hold Switch button for 8s to reset the Switch and get into quick configure mode

Select the Wi-Fi and enter the password then click Next

Wait for completing the connection.

STEP 4 Control switch with APP

All added devices can be viewed in the main menu of the APP

08 Reset

Press and hold Switch button for 8s to reset the Switch and get into quick configure mode

STEP 5 Enable the skill

Login the account you registered on the App in Part 2, then click "Link Now"

10 Smart Life Skills (Google)

Find "Home Control" in the hamburger menu on the Google Home app's home page > Home Control > tap "+"

After you assign rooms for the Switch, your Switch will be listed in the Home Control page

Control your smart switch through Google Home

Now you can control your smart switch through Google Home.

If you set the name as "bedroom light", the supported voice commands are as below:

Ok Google, turn on bedroom light.

Ok Google, set bedroom light to 50%.

IC Caution

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) This device may not cause interference, and (2) This device must accept any interference, including interference that may cause undesired operation of the device.

FCC Caution

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) This device must accept any interference received, including interference that may cause undesired operation.

09 Smart Life Skills (Alexa)

Log in your Alexa account on a smart phone or a computer, then tap Home-Skills & Games

Search "Smart Life" and select the right one according to the blue logo (same with App)

STEP 6 Congratulations! Alexa Devices (Echo) can Control the Switch ON/OFF.

To add or delete switches, please delete or add them in the Smart Life App (See Part 2) and then the Alexa will synchronize automatically.

If you cannot see the name of switches in the Devices List in Alexa Page, You can click "Discover" in Alexa page It will synchronize from the Smart Life App.

STEP 3.2 Troubleshooting

Make sure you have good Wi-Fi signal strength at the location of the switch

Metal box and MATEL Surface-wall board may block Wi-Fi signal

Make sure input correct Wi-Fi password

07 Add Devices

Please scan QR code and download the Smart Life app iOS or Android version

Enter the Register/Login interface; tap "Register" to create an account by entering your phone number to get verification code and "Set password", Choose "Log in" if you already have a Smart Life account some third-party accounts log in directly.

200X455MM 四色印刷 80g哑光纸 风琴折

