

Maedhawk Bluetooth Car Kit - BTR005

MAEDHAWK
Focus on Connecting

BTR005


WIRELESS ADAPTER User Guide

Please read this guide carefully and keep it for future reference.

Package contents

·BT Receiver ·Micro USB Charging cable ·User Manual

Product Overview



- 1.Multifunction button with LED indicator
- 2.3.5mm jack plug
- 3.Micro USB port
- 4.Microphone

Specifications

S/N	92dB
Bluetooth	V5.0,A2DP,AVCP
Bluetooth Range	Up to 15 meters
Frequency Response	20Hz-22KHz
Play Time	Up to 5 hours
Charging Time	1.5 Hours
Charging Voltage	DC 5V/1A

Instructions for use Getting started

- To turn the receiver on press and hold the MFB(1) for 3 seconds
- To turn the receiver off press and hold the MFB(1) for 3 seconds
- The unit will shut down automatically if no action in 10 minutes

Charging

It is recommended that fully charge it before its first use.

- 1.Plug the micro USB end of the charge cable into the micro USB Charging port(2) of the Receiver
- 2.Plug the standard USB cable end into either a computer or a USB mains charger
- 3.The MFB(1) will be solid red whilst charging
- 4.When charging is complete the MFB(1) will be solid blue

Pairing the receiver to your device

**It will need to be paired to your device before using it
To do this:**

- 1.Press and hold the MFB(1) for 3 seconds .
This will turn the receiver on and automatically enter pairing mode.
The MFB(1) will fast flash blue and red when in pairing mode.
- 2.Turn your device's Bluetooth ON and search for new devices
- 3.When the "MaedHawk BTR005" appears in the list,select it and if it asks for a passcode,just enter '0000'.
- 4.The receiver should then be paired to your device.
- 5.The receiver wil automatically pair to the last device it connected to when turned on.

Pairing mode will be active for 3 minutes. After this,the light will slowly flash blue.TO re-activate pairing mode,turn the receiver off and follow the instructions as above.
Please note you can have two devices paired to the BT Receiver at any time.

If you can Not find the paring name "MaedHawk BTR005" on your cell phone,please read the no.1 carefully and pay attention to below:
[DO NOT release your hand on 3 seconds when the led red and Blue flash only for 1 time]

Pair with 2 cell phones simultaneously

- 1.Make the Receiver pair with your 1st phone sucessfully,then disconnect them(disable bluetooth of the phone).
- 2.Make it re-enter pairing mode and pair with the 2nd phone.
- 3.Enable Bluetooth of the 1st phone and tap "MaedHawk BTR005" in the list to connect.
- 4.will automatically connect this both phones next time once it power on.

Playing music through your receiver Aux-in/Bluetooth

If already connector to the receiver via Bluetooth,simply plug The BT Receiver into the aux-in port of the speaker/stereo.
Whilst playing music,please use your device to change volume/track.
To play/pause songs through the receiver,short press the MFB(1).

Call handing

The receiver can also take and receive calls when connected.

Answer phone call short press MFB(1)
Reject phone call press MFB(1) for 1 second
Hang up the call short press MFB(1)
Redial last number short press MFB(1) twice
Cancel dialing short press MFB(1)

Note:

If your aux-in port is located within the glove box and the Glove box is closed,you may have problems talking over the Phone as the MIC won't be able to pick up your voice.

Battery

- Low battery alarm will indicate there is 5 minutes left of battery
- After 5 minutes the BT Receiver will turn off

WARRANTY

Please rest assured that our product is guaranteed for 12 months.

Please contact us if you have any questions or need any help




[Your 100% Satisfaction Is Our Eternal Pursuit]

FCC Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- 1.Reorient or relocate the receiving antenna.
 - 2.Increase the separation between the equipment and receiver.
 - 3.Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
 - 4.Consult the dealer or an experienced radio/TV technician for help
- This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions (1)this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.



We apologise for any inconvenience caused by minor inconsistencies in these Instructions,which may occur as result of product improvement and development.

360*90mm