

F26070636

KTC® 设计稿、样稿确认

(相同样稿以最新承认日期为准)

物料编号: _____

物料描述: HG-P1 (HG-P1A) HORIZON-电商 投屏器 英文说明书 (2P风琴折页, 成品尺寸74×105mm, 展开尺寸370×105mm, 需符合TSCA)

设计申请人: _____ 设计人: 谭文文

承认人: _____ 承认日期: _____

备注: 整本四色印刷, 105g哑粉纸, 不过膜 不压纹, 正反两面印刷

不印刷KTC料号及料号二维码

在7311-HGP100-60308861设计单基础上添加FCC标语、QC PASS章

严禁供应商私自修改调整KTC文件, 如文件和印刷工艺有冲突需要调整, 请联系KTC 设计师或RE 确认修改方案

折叠效果示意图

105 mm

封面

Product Introduction

1. This wireless display adapter comes as a complete transmitter and receiver set, and also features built-in direct cast mode for flexible usage.
2. It supports two working modes: transceiver-based synchronous casting and standalone direct cast mode.
3. In direct cast mode, the receiver can work independently without the transmitter, mirroring your device screen in real time with no network configuration required.

Scan the QR code to view
Product Use Video Demonstration

Product list

Basic Parameters

Product name: Transmitter & Receiver Kit
Product model: HG-P1A
Product color: White
Resolution: 1080P 60 Hz
Supported Operating Systems:
Windows: Windows10 and above
Android: Android7.0 and above
IOS: IOS 12.0 and above
Mac: Mac OSX 10.11 and above

Product Description

Receiver Indicator Status:
Solid blue light: Receiver powered on and ready.

Transmitter Indicator Status:
Blinking blue light: Transmitter powered on, auto-pairing with receiver in progress.
Solid blue light: Transmitter paired successfully with receiver, mirroring starts.

Usage Introduction

Connect display device:

- Power on the receiver.
- Connect the receiver to your display device with an HDMI cable.
- Select the corresponding HDMI input source on the display device.

Connection method ①:

1. Insert the transmitter into the Type-C port of devices that support DisplayPort (DP) signal output;

2. Wait until the transmitter indicator light turns solid blue, indicating successful connection, and screen mirroring will begin automatically.
(The transmitter and receiver are pre-paired by factory default.)
3. During screen mirroring, press the transmitter button to stop mirroring; press again to resume.

Landscape & Portrait Switching

Support landscape / portrait screen switching:

Press the button on the receiver to switch between landscape and portrait modes.

Display device

Display device

FAQ

Q: There' s nothing on the display.

A: Please check whether the display device switch to the correct HDMI source or the receiver is in charging or not. When the receiver is in charging, the indicator light will be solid blue. After switching the display device to the correct HDMI source, the display device screen will jump to the software interface of the screen mirror.

Q: What are the differences between the two connection methods for the wireless display adapter?

A: ① Transmitter-connected screen mirroring
Requires the connected device to have a DisplayPort video output interface. Simply plug in to start mirroring instantly.

② Standalone receiver screen mirroring
Supports Miracast and AirPlay protocols, and is compatible with most mainstream devices.

Q: After connecting the transmitter to the phone, the indicator light stays on, but why is there no image on the display?

A: If your phone does not support DisplayPort video output, the transmitter will fail to work. You may try another screen mirroring method or use a different compatible device.

Notes

1. **Optimal Mirroring Distance:** To ensure stable and high-quality mirroring effect, it is recommended that there are no obstructions within the straight-line distance between the source device and the display during transmission.
2. **Type-C Mirroring Requirement :** When using the Type-C transmitter for screen mirroring, the connected device must support DisplayPort video output; otherwise, Type-C mirroring will be unavailable.
3. **After-sales Service:** If screen mirroring fails, please refer to the solutions in the FAQ section. If the issue persists, contact our technical support team for further assistance.

Quality Certificate

Product: Transmitter & Receiver Kit
This product has been inspected by our company's Quality Control and Quality Assurance departments. Its performance parameters comply with the technical standards and it is approved for shipment.

FCC Statement

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1)This device may not cause harmful interference.
(2)This device must accept any interference received, including interference that may cause undesired operation.
2. Changes or modifications not expressly approved by the party responsible for compliance could void the user' s authority to operate the equipment.
Note: This equipment has been tested and found to comply with the limits for a class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. This equipment should be installed and operated with a minimum distance of 20 cm between the radiator and your body. (For product: Wireless Display Adapter)

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.(For product: Transmitter & Receiver Kit)

The terms HDMI, HDMI High-Definition Multimedia Interface, HDMI Trade dress and the HDMI Logos are trademarks or registered trademarks of HDMI Licensing Administrator, Inc.

74 mm

沿中间红色虚线折叠 (红色虚线不印刷)