SHARGE闪极

SHARGE - M8-磁吸移动电源 说明书

尺寸：//（整体高度）
颜色：CMYK
材质：80g哑粉纸
工艺：

85 mm

55 mm

磁吸无线充移动电源M8

产品使用说明书

SHARGE

包装清单

- 移动电源 × 1
- 说明书 × 1
- 充电线 × 1

产品参数

产品名称：移动电源
产品型号：M8
接口类型：USB-C
额定输入电压、电流：USB-C：5V—3A，9V—1.67A
额定输出电压、电流：USB-C：5V—3A，9V—2.22A；
无线输出：15W
总输出：5V—3A
额定能量：18.5Wh 5000mAh 3.7V
额定容量：3000mAh（5V—2.4A）
电池组代号：1INP7/65/79
FCC ID：2BBZZ-M8
转换效率：>70%
产品重量：≈140g
产品尺寸：102 × 72 × 11.7mm
执行标准：GB 4943.1-2022/GB 31241-2022

操作指南

设备充电
将移动电源的USB-C接口连接到电源适配器。



给手机无线充电
01. 把设备放在手机背面，就可以自动吸附并为手机充电。无线充电时，屏幕显示

给手机有线充电
01. 使用充电线连接磁吸无线充移动电源和您的手机。

屏幕显示与状态说明

SHARGE **开机显示**
短按按键，屏幕点亮并显示品牌界面。

100 **查看电量**
短按按键，可查看当前剩余电量。

75 CC 20W Output **USB-C输出**
使用USB-C数据线设备时，屏幕会显示当前电量与输出功率。

100 CC 20W Input **USB-C输入**
给移动电源充电时，屏幕会显示当前电量与输入功率。

iPhone 17 Pro Max **磁吸无线充电**
将手机放到智能底座，可自动开始无线充电，并显示识别到的设备型号。

100 CC 15W Output **无线输出**
磁吸无线充电时，屏幕会显示无线输出功率。

100 CC 3.5W C1 5W **边充边用**
移动电源在充电的同时，也可以继续为手机进行磁吸无线充电。

100 CC 3.5W C1 5W **双路输出**
USB-C与无线充可同时为两台设备供电。

OTP **过温保护显示**
当移动电源温度过高时，屏幕显示 OTP 提示 5 秒后熄灭，请保持使用并静置冷却，若故障未排除，短按按键后将再次显示。

注意事项

当移动电源进行无线输出时，如检测到金属异物，屏幕将显示 FOD 图标并于 5 秒后熄灭，经异物未移除，短按按键重新唤醒屏幕后，将再次显示 FOD 图标 5 秒。

注意:电源请勿与带有磁条或芯片的证卡（身份证,银行卡等）放置太近,以免磁卡失效。

异物检测保护

售后服务

SHARGE 售后服务严格依照《中华人民共和国消费者权益保护法》、《中华人民共和国产品质量法》实行售后三包服务。
服务内容如下：
在三包有效期内，您可以依照本规定免费享受退货、换货、维修的服务。
维修、换货、退货应当优先复原办理。
01. 7日无理由退货，由用户承担物流费用。
02. 本产品出现「产品性能故障表」所列性能故障的情况，经检测确定后，可免费享受如下服务。

服务类型	服务政策
退货	自签收次日起7天内产品质量原因退货服务
换货	自签收次日起15天内产品质量原因换货服务
维修	自签收次日起一年内产品质量原因维修

非保修条例

01. 未经授权的维修、误用、碰撞、跌落、进水、事故、改动、不正确地使用程序。
02. 已超过三包有效期。
03. 因不可抗力因素造成的损坏。
04. 不符合「产品性能故障表」所列性能故障的情况。
05. 因人为原因导致本产品产生「产品性能故障表」所列性能故障。

产品性能故障表

类别	性能故障
移动电源	01. 因结构或材料因素造成的外壳裂损。 02. 无法显示电量。 03. 无法为电子设备充电。

产品安全信息

01. 将本产品存放在阴凉干燥处。
02. 请勿将本产品存放在高温或潮湿的环境中。
03. 使用非本产品制造商推荐或出售的电源或充电器会导致火灾或人员受伤风险。
04. 使用环境温度介于 32 至 95°F （0 至 35°C ）。
05. 禁止拆解、撞击、挤压或投入火中。
06. 如果本产品长时间不使用，应每三个月补充一次电量。
07. 充电时，本产品可能会发热。这是正常现象，无需担心。
08. 在正常操作情况下，电池性能会在几年内逐渐下降。
09. 切勿置于高温环境中。
10. 请勿使用有害化学品或清洁剂清洁本产品。
11. 使用不当，频繁或过度地刀切会损坏电池本产品损坏。
12. 切勿拆卸电池，请将不同电化学体系的电池分开。
13. 若出现严重鼓胀，切勿继续使用。
14. 注意：如果更换为错误类型的电池，则有爆炸风险。
15. 警告：电池（电池包或安装的电池）不得暴露在过热的环境中，例如阳光下或火中。
16. 电池在吸收气压下可能发生爆炸或出现易燃液体或气体泄漏。
17. 请长时禁止使用。
18. 消费者若使用电源适配器供电，则应购买配套使用满足相应安全标准要求并获得CCC认证的电源适配器。

电子信息产品有毒有害物质申明

部件名称	有毒有害物质或元素					
	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr VI)	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
PCB	X	O	O	O	O	O
塑胶	O	O	O	O	O	O
金属	X	O	O	O	O	O
附件	O	O	O	O	O	O

电子信息产品有毒有害物质申明
本表格依据 SJ/T 11364 的规定编制。
O: 表示该有毒有害物质在该部件所有均质材料中的含量均在 GB/T 26572 标准规定的限量要求以下。
X: 表示该有毒有害物质至少在该部件某一均质材料中的含量超出 GB/T 26572标准规定的限量要求。
本表格信息基于供应商提供的数据及符合 RoHS 环保要求的检测结果。

制造商: 闪极科技（深圳）有限公司
地 址：深圳市龙华区龙华街道油松社区恒丰小区3号楼新中泰工业园3楼305室
生产厂商：高雷达（广东）充电有限公司
官方网址：www.shARGE.com
联系方式：400-075-5501

此包装袋和本产品不得作为生活垃圾处理，相反，应将其交付经适用的收集点进行电子设备回收。

RoHS Made in China 中国制造

5年质保 合格证 已检验

Join our Discord SHARGE

Follow us on Instagram @SHARGE_OFFICIAL

官方微信 官方抖音

Magnetic Wireless Power Bank

USER MANUAL

SHARGE

Package Contents

- Power Bank × 1
- User Manual × 1
- Cable × 1

Product Information

Product Name: Power Bank
Model: M8
Port type: USB-C
Rated Energy: 18.5Wh 5000mAh 3.7V
Rated Capacity: 3000mAh (5V—2.4A)
Input:
USB-C: 5V—3A, 9V—1.67A
Output:
USB-C: 5V—3A, 9V—2.22A
Wireless Output: 15W
Total Output: 5V—3A
Conversion rate: >70%
FCC ID: 2BBZZ-M8
Battery Pack Code: 1INP7/65/79
Dimensions: 102 × 72 × 11.7mm
Weight: ≈140g
Manufacturer: Shargе Technology (Shenzhen) Co., Ltd.
Address: Room 305, Floor 3, Xinhongjui Industrial Park, Building 3, Hengfeng Residential Quarter, Youxiang Community, Longhua Sub-District, Longhua District, Shenzhen
Producer: Guangdong Gaopai Group Co., Ltd.
Official Website: www.shARGE.com E-mail: info@shARGE.com
Contact: 400-075-5501

Quick start Guide

Charging the Power Bank
Connect the USB-C port of the power bank to a power adapter using a USB-C charging cable.



Wireless Charging for Your Phone
Attach your phone to the magnetic charging area on the back of the power bank. It will automatically align and start wireless charging. The screen will display the current working status during wireless charging.

Wired Charging for Your Phone
Connect your phone to the power bank using a USB-C charging cable to start wired charging.

Screen Display & Status Description

SHARGE **Power-on Display**
Short press the button to wake the screen and display the brand logo.

100 **Battery Level**
Short press the button to check the current remaining battery level.

75 CC 20W Output **USB-C Output**
When a device is connected via USB-C, the screen displays the current battery level and output power.

100 CC 20W Input **USB-C Input**
When the power bank is being charged, the screen displays the current battery level and input power.

iPhone 17 Pro Max **Magnetic Wireless Charging**
After the phone is magnetically attached to the back of the power bank, wireless charging starts automatically and the detected device model will be displayed.

100 CC 7.5W Output **Wireless Output**
During magnetic wireless charging, the screen displays the current wireless output power.

100 CC 3.5W C1 5W **Pass-through Charging**
The power bank can continue to wirelessly charge your phone while it is being charged.

100 CC 3.5W C1 5W **Dual Output**
USB-C and wireless charging can power two devices at the same time.

OTP **Over-temperature Protection**
When the power bank temperature is too high, the screen displays the OTP warning for 5 seconds and then turns off. Stop using the device and allow it to cool down. If the issue remains, short press the button to wake the screen and the warning will appear again.

Foreign Object Detection Protection

When the power bank is wirelessly charging and a metal foreign object is detected, the screen displays the FOD icon for 5 seconds and then turns off. If the foreign object is not removed, short press the button to wake the screen and the FOD icon will be displayed again for 5 seconds.

Note: Do not place cards with magnetic strips or chips, such as ID cards or bank cards, between the power bank and the phone, as this may affect magnetic alignment or cause card failure.

Foreign Object Detection Protection

Product Safety Information

Before using this product, please read all instructions and warnings. Improper use may result in damage to the product or personal safety.

01. Store this product in a cool, dry place.
02. Do not store this product in high-temperature or humid environments.
03. Use of power supply or chargers not recommended or sold by the manufacturer may result in fire or risk of injury to persons.
04. Ambient temperature for use: 32°F to 95°F (0°C to 35°C).
05. Do not disassemble the product. If the product needs service or repair, please contact qualified service persons. Incorrect reassembly may cause a fire or risk of injury to persons.
06. To maintain battery health, it's advisable to recharge the product every three months if it's not in use for an extended period.
07. When charging a device, the product may feel warm. This is a normal condition and should not be a cause for concern.
08. Battery performance will decline over several years under normal operating conditions.
09. Do not dispose of the product in heat or fire.
10. Do not clean this product with harmful chemicals or detergents.
11. Misuse, dropping, or excessive force may cause damage to the product.
12. When disposing of secondary cells or batteries, keep cells or batteries of different electrochemical systems separate from each other.
13. Note that discharged batteries may cause fires or smoke.
14. Be aware that if the battery (battery pack or installed battery) is replaced with incorrect types, there may be a risk of explosion.
15. Be aware that the battery (battery pack or installed battery) must not be exposed to excessive heat environments such as sunlight or fire.
16. Batteries may explode or leak flammable liquid or gas at extremely low pressure.
17. Do not use after immersion in water.

Product Performance Failure

Product Type	Performance failure
POWER BANK	01. Cracks in the shell caused by structural or material factors. 02. Unable to display battery level. 03. Unable to charge electronic devices.

Customer Service

The following services are available for you to enjoy free of charge according to this policy: returns, exchanges, and repairs. Repairs, exchanges, and returns must be processed with a receipt.

01. Within 7 days of receipt, you may return the product without reasons, but you must bear the shipping costs.
02.12-month warranty in the event that the product experiences any performance failure, as specified in the "Product Performance Failure" list, and is duly confirmed upon inspection.

Exclusions from Warranty

01. Unauthorized repairs, misuse, collision, negligence, abuse, liquid ingress, accidents, modifications, and incorrect use of accessories.
02. The warranty period has expired.
03. Damages caused by force majeure factors.
04. Cases that do not meet the performance faults listed in the Product Performance Failure".
05. Performance failure listed in the "Product Performance Failure" caused by human factors.

Declaration of Toxic and Hazardous Substances in Electronic Products

PART NAME	TOXIC AND HAZARDEOUS SUBSTANCE AND ELEMENTS					
	Pb	Hg	Cd	Cr6+	PBB	PBDE
PCB	X	O	O	O	O	O
PLASTICS	O	O	O	O	O	O
METALST	X	O	O	O	O	O
COMPONENTS	O	O	O	O	O	O

This table is prepared in accordance with the provisions of SJ/T 11364.
O: Indicates that the content of the toxic and hazardous substance in all homogeneous materials of the component is below the limit specified by GB/T 26572.
X: Indicates that the content of the toxic and hazardous substance exceeds the limit specified by GB/T 26572 in at least one homogeneous material of the component.
The information in this table is provided to suppliers in the form of data and testing results that comply with RoHS environmental requirements.

FCC Warning Statement

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1)This device may not cause harmful interference, and
(2)This device must accept any interference received, including interference that may cause undesired operation.

FCC Radiation Exposure Statement

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

变更日期	变更内容	变更日期	内容	备注
				技术要求: 公差: ±0.5mm 印刷清晰无露白及毛刺过膜平滑 不起皱所有材质必须符合RoHS规范

机密文件版权所有为深圳市闪极科技有限公司
抄袭、篡改、擅自外泄将追究法律责任

闪极科技（深圳）有限公司

产品型号	版本号	设计师	审核	制表日期
M8	A	周良哲	廖军军	2026/04/28
备注				