

NOCO BOOSTHD GB70

User Guide & Warranty

For more information and support visit: www.no.co/support

DANGER

READ AND UNDERSTAND ALL SAFETY INFORMATION BEFORE USING THIS PRODUCT.

Failure to follow these safety instructions may result in ELECTRICAL SHOCK, EXPLOSION, FIRE, which may result in a SERIOUS INJURY, DEATH, or PROPERTY DAMAGE.

Electrical Shock. Product is an electrical device that can shock and cause serious injury. Do not cut power cords. Do not submerge in water or get wet.

Explosion. Unmonitored, incompatible, or damaged batteries can explode if used with product. Do not leave product unattended while in use. Do not attempt to jump start a damaged or frozen battery. Use product only with batteries of recommended voltage. Operate product in well ventilated areas.

Fire. Product is an electrical device that emits heat and is capable of causing burns. Do not cover product. Do not smoke or use any source of electrical spark or fire when operating product. Keep product away from combustible materials.

Eye Injury. Wear eye protection when operating product. Batteries can explode and cause flying debris. Battery acid can cause eye and skin irritation. In the case of contamination of eyes or skin, flush affected area with running clean water and contact poison control immediately.

Explosive Gases. Working in the vicinity of a lead- acid is dangerous. Batteries generate explosive gases during normal battery operation. To reduce risk of battery explosion, follow all safety information instructions and those published by the battery manufacturer and manufacturer of any equipment intended to be used in the vicinity of battery. Review precautionary markings on these products and on engine.

IMPORTANT SAFETY WARNINGS

Proposition 65. Battery posts, terminals and related accessories contain chemicals known to the State of California to cause cancer and birth defects or other reproductive harm. Wash hands after handling.

Personal Precautions. Use the product only for its intended purpose. Someone should be within range of your voice or close enough to come to your aid in case of an emergency. Have a supply of clean water and soap nearby in case battery acid contamination occurs. Wear complete eye protection and protective clothing while working near a battery. Always wash hands after handling batteries and related materials. Do not handle or wear any metal objects while working with

batteries, including; tools, watches or jewelry. If metal falls on the battery, it may generate a spark or create a short circuit resulting in electrical shock, fire, explosion, which may result in injury, death or property damage.

Minors. If the “Purchaser” intends for the product to be used by a minor, the purchasing adult agrees to provide detailed instructions and warnings to any minor prior to use. Failure to do so is the sole responsibility of the “Purchaser”, who agrees to indemnify NOCO for any unintended use or misuse by a minor.

Choking Hazard. Accessories may present a choking hazard to children. Do not leave children unattended with the product or any accessory. The product is not a toy.

Handling. Handle the product with care. The product can be damaged if impacted. Do not use a damaged product, including but not limited to, cracks in the enclosure or damaged cables. Do not use the product with a damaged power cord. Moisture and liquids can damage the product. Do not handle the product or any electrical components near any liquid. Store and operate the product in dry locations. Do not operate the product if it gets wet. If the product is already operating and becomes wet, disconnect it from the battery and discontinue use immediately. Do not disconnect the product by pulling the cables.

Modifications. Do not attempt to alter, modify or repair any part of the product. Disassembling the product may cause injury, death or property damage. If the product is damaged, malfunctions or comes into contact with any liquid, discontinue use and contact NOCO. Any modifications to the product will void your warranty.

Accessories. This product is approved for use only with NOCO accessories. NOCO is not responsible for user safety or damage when using accessories not approved by NOCO.

Location. Prevent battery acid from coming into contact with the product. Do not operate the product in an enclosed area or an area with restricted ventilation. Do not place a battery on top of the product. Position cable leads to avoid accidental damage by moving vehicle parts (including hoods and doors), moving engine parts (including fan blades, belts and pulleys), or anything that may become a hazard that can cause injury or death.

Operating Temperature. This product is designed to operate in ambient temperatures between -20°C to 50°C. Do not operate outside of temperature ranges. Do not jump start a frozen battery. Discontinue use of the product immediately if the battery becomes excessively hot.

Storage. Do not use or store your product in areas with high concentrations of dust or airborne materials. Store your product on flat, secure surfaces so it is not prone to falling. Store your product in a dry location. The storage temperature is -20°C - 50°C (0°C to +25°C Avg Temp.). Never exceed 80°C under any circumstances.

Compatibility. The product is only compatible with 12-volt lead-acid batteries. Do not attempt to use the product with any other type of battery. Jump starting other battery chemistries may result in injury, death or property damage. Contact the battery manufacturer before attempting to jump start

the battery. Do not jump start the battery if you are unsure of the specific battery chemistry or voltage.

The Battery. The lithium-ion battery integrated into the product should only be replaced by NOCO and must be recycled or disposed of separately from household waste. Do not attempt to replace the battery yourself and do not handle a damaged or leaking lithium-ion battery. Never dispose of the battery in the trash. Disposal of batteries in the trash is unlawful under state and federal environmental laws and regulations. Always take used batteries to your local battery recycling center. If the product battery becomes excessively hot, emitting an odor, deformed, cut, or is demonstrating an abnormal occurrence, discontinue all use immediately and contact NOCO.

Charging the Battery. Charge the product with the included USB Charge Cable and the NOCO 10W 12V power adapter. A third-party USB cable and 5W or 10W power adapter that are compatible with USB 2.0 or power adapters that are compliant with one or more of the following standards EN 301489-34, IEC 62684, YD/T 1591-2009, CNS 15285, ITUL.2000. Be cautious with the use of low-quality power adapters, as they may present a serious electrical risk which can result in injury to person, device, and property. If using a third-party USB power adapter, contact the manufacturer(s) to find out if your power adapter is in compliance with the above standards. The use of damaged cables or chargers, or charging when moisture is present, can result in electrical shock. The use of generic or third-party power adapters may shorten the life of your product and cause the product to malfunction. NOCO is not responsible for user safety when using accessories or supplies not approved by NOCO. When using a USB Power Adapter to charge the product, make sure the AC plug is fully inserted into the adapter before plugging into a wall outlet. Power adapters may become warm during normal use and prolonged skin contact may cause bodily injury. Always allow for adequate ventilation around power adapters when using them.

To ensure maximum battery life, avoid charging your product for more than a week at a time, as overcharging may shorten battery life. Over time, an unused product will discharge and must be recharged before use. Disconnect the product from power sources when not in use. Use the product only for their intended purposes.

Medical Devices. Product may emit electromagnetic fields. Product contains magnetic components which may interfere with pacemakers, defibrilators, or other medical devices. These electromagnetic fields may interfere with pacemakers or other medical devices. Consult with your physician prior to use if you have any medical device including pacemakers. If you suspect the product is interfering with a medical device, stop using the product immediately and consult your physician.

Medical Conditions. If you have any medical condition that you believe could be affected by product, including but not limited to; seizures, blackouts, eyestrain or headaches, consult your physician prior to use of product. The use of a integrated high-powered flashlight contains a light sensitivity hazard. Use of the light in Strobe Mode may cause seizures in persons with photosensitive epilepsy, which may result in serious injury or death.

Light. Staring directly into the light beam or shine of the flashlight may result in permanent eye injury. The product is equipped with a high output LED pre-focused lamp that emits a powerful beam at the highest setting.

Cleaning. Power off the product before attempting any maintenance or cleaning. Clean and dry product immediately if it comes in contact with liquid or any type of contaminant. Use a soft, lint-free (microfiber) cloth. Avoid getting moisture in openings.

Explosive Atmospheres. Obey all signs and instructions. Do not operate product in any area with a potentially explosive atmosphere, including fueling areas or areas which contain chemicals or particles such as grain, dust or metal powders.

High-Consequence Activities. This product is not intended for use where the failure of the product could lead to injury, death or severe environmental damage.

Radio Frequency Interference. Product is designed, tested, and manufactured to comply with regulations governing radio frequency emissions. Such emissions from the product can negatively affect the operation of other electronic equipment, causing them to malfunction.

Model Number: GB70 This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

How to Use

Step 1: Charge the GB70.

The GB70 comes partially charged out of the box and needs to be fully charged prior to use. Connect the GB70 using the included USB Charge Cable to the USB IN port and the USB car charger. It can also be recharged from any USB powered port, like an AC adapter, car charger, laptop and more. The USB IN port is rated at 2.1 Amps to ensure safe and efficient charging of the internal lithium battery. Due to FCC regulations, we recommend not to charge and discharge the unit at the same time. The time to recharge a GB70 will differ based on the discharge level and the power source used. Actual results may vary due to battery conditions.

Charger Rating: .5A, 1A, 2A

Recharge Time: 28hr, 14hr, 7hr

12V Fast Charge: 3A @ 12V (36W) 2-3hr



When recharging, the charge level of the internal battery is indicated by the Charge LEDs. The LEDs will slowly pulse 'On' and 'Off' and become solid until all four Charge LEDs are on. When the battery is fully charged, the Green (100%) LED will be solid, and the (25%) (50%) and (75%) Charge LEDs will turn "Off". From time to time, the Green (100%) LED will pulse indicating maintenance charging is occurring.

USB Charging (Up to 10W): Connect the GB70 using the included USB Charge Cable to the USB IN port and a powered USB port, like an AC adapter, car charger, laptop and more. The USB IN port is rated at 2.1 Amps to ensure safe and efficient charging of the internal lithium battery.

12V Fast Charge (36W): Connect the 12V Cable to the 12V IN port on the GB70, and the other end to the Male 12 Plug. Plug into a powered 12V AUX Plug (Cigarette Lighter Port.)

Powering Your 12V Devices.

Connect the 12V Cable to the "12V OUT" port on the GB70, and the other end to the Female 12V Plug (12V AUX/ Cigarette Lighter Port.) Plug-in any standard 12V device (Up to 15A) with a 12V plug and turn the GB70 "On" to start powering your device.

Step 2: Connect to the Battery.

Carefully read and understand the vehicle owner's manual on specific precautions and recommended methods for jump starting the vehicle. Make sure to determine the voltage and chemistry of the battery by referring to your battery owner's manual prior to using this product. The GB70 is for jump starting 12-volt lead-acid batteries only. Before connecting to the battery, verify that you have a 12-volt lead-acid battery. The GB70 is not suitable for any other type of battery, identify the correct polarity of the battery terminals on the battery. The positive battery terminal is typically marked by these letters or symbol (POS.P+). The negative battery terminal is typically marked by these letters or symbol (NEG.N-). Do not make any connections to the car, fuel, tires, or thin, sheet metal parts. The below instructions are for a negative ground system (most common). If your vehicle is a positive ground system (very uncommon), follow the below instructions in reverse order.

- 1.) Connect the positive (red) HD battery clamp to the positive (POS,P,+) battery terminal.
- 2.) Connect the negative (black) HD battery clamp to the negative (NEG,N,-) battery terminal or vehicle chassis.
- 3.) When disconnecting, disconnect in the reverse sequence, removing the negative first (or positive first for positive ground systems).

Step 3: Jump Starting.


- 1.) Make sure all of the vehicle's power loads (headlights, radio, air conditioning, etc.) are turned off before attempting to jump start the vehicle.
- 2.) Press the Power Button to begin jump starting. All LEDs will flash, indicating that all LEDs are properly functioning. If you are properly connected to the battery, the White Boost LED will illuminate. If the battery clamps are connected in reverse, the Red Error LED will illuminate. Reverse the connections to clear this error and then the White Boost LED will illuminate. The White Boost LED is illuminated, when the GB70 is ready to jump start your vehicle.
- 3.) Try starting the vehicle. Most vehicles will immediately start. Some vehicles may require the GB70 to be connected for up to 30 seconds before starting. If the vehicle does not start right away, wait 20-30 seconds and try again. Do not attempt more than five (5) consecutive jump starts within a fifteen (15) minute period. Allow the GB70 to rest for fifteen (15) minutes before attempting to jump start the vehicle again.
- 4.) Once you have started your vehicle, disconnect the battery clamps, and remove the GB70.

Low Voltage Batteries & Manual Override.

The GB70 is designed to jump start 12-volt lead-acid batteries down to 2-volts. If your battery is below 2-volts, the Boost LED will be "Off". This is an indication that the GB70 can not detect a battery. If you need to jump start a battery below 2-volts there is a Manual Override feature, which allows you to force "On" the jump start function.

CAUTION. USE THIS MODE WITH EXTREME CARE. THIS MODE IS FOR 12-VOLT LEAD-ACID BATTERIES ONLY. BOTH THE SPARK PROOF AND REVERSE POLARITY PROTECTION FEATURES ARE DISABLED. PAY VERY CLOSE ATTENTION TO THE POLARITY OF THE BATTERY BEFORE USING THIS MODE. DO NOT ALLOW THE POSITIVE AND NEGATIVE BATTERY CLAMPS TO TOUCH OR CONNECT TO EACH OTHER AS THE PRODUCT WILL GENERATE SPARKS. THIS MODE USES VERY HIGH CURRENT (UP TO 2000 AMPS) THAT CAN CAUSE SPARKS AND HIGH HEAT IF NOT USED PROPERLY. IF YOU ARE UNSURE ABOUT USING THIS MODE, DO NOT ATTEMPT AND SEEK PROFESSIONAL HELP.

Features



- 1.) Internal Battery Level Indicates the charge level of the internal battery.
 - 2.) Error LED Illuminates Red if reverse polarity is detected, or blinks "On" and "Off" when the internal battery temperature is too high.
 - 3.) Power Button Push to turn unit "On" & "Off".
 - 4.) Power LED Illuminates White when unit is "On".
 - 5.) Light Mode Button Toggles the ultra-bright LED light through 7 light modes: 100% > 50% > 10% > SOS > Blink > Strobe > Off
 - 6.) Boost LED Illuminates White when Boost is active. If the unit is connected properly to a battery, the GB70 will automatically detect a battery and go into Boost mode (LED flashes White when Manual Override feature is active).
 - 7.) Manual Override Button To enable, push and hold for three (3) seconds. **WARNING:** Disables safety protection and manually forces Boost "On". Only for use when a battery is too low to be detected.
-

Troubleshooting

Error	Reason/Solution
Error LED: Solid Red	Reverse polarity/Reverse the battery connections.
Error LED: Blinking Red w/Cables Connected Properly	The internal battery is too hot/Allow the unit to cool. Bring the unit into cooler environment.
Boost Light Does Not Come On w/ Cables Connected Properly	Connected battery is below 2-volts/Remove all loads, and try again, or use Manual Override Mode.

Technical Specifications

Internal Battery: Lithium Ion

Peak Current Rating: 2000A

Operating Temperature: -20°C to +50°C

Charging Temperature: 0°C to +40°C

Storage Temperature: -20°C to +50°C (Avg Temp.)

Micro USB (Input): 5V, 2.1A

USB (Output): 5V, 2.1A

12V (Input): 12V, 3A

12V (Output): 12V, 15A

Housing Protection: IP65 (w/Ports Closed)

Cooling: Natural Convection

Dimensions (L x W x H): 8.6 x 6 x 2.5 Inches

Weight: 5 Pounds

Warranty

NOCO One (1) Year Limited Warranty.

The NOCO Company ("NOCO") warrants that this product ("Product") will be free from defects in material and workmanship for a period of one (1) year from the date of purchase (the "Warranty Period"). For defects reported during the Warranty Period, NOCO will, at its discretion, and subject to NOCO's technical support analysis, either repair or replace defective Product. Replacement parts and products will be new or serviceably used, comparable in function and performance to the original part and warranted for the remainder of the original Warranty Period.

NOCO'S LIABILITY IS EXPRESSLY LIMITED TO REPLACEMENT OR REPAIR. TO THE MAXIMUM EXTENT PERMITTED BY LAW, NOCO SHALL NOT BE LIABLE TO ANY

PURCHASER OF THE PRODUCT OR ANY THIRD PARTY FOR ANY SPECIAL, INDIRECT, CONSEQUENTIAL OR EXEMPLARY DAMAGES, INCLUDING BUT NOT LIMITED TO, LOST PROFITS, PROPERTY DAMAGE OR PERSONAL INJURY, RELATED IN ANY WAY TO THE PRODUCT, HOWSOEVER CAUSED, EVEN IF NOCO HAD KNOWLEDGE OF THE POSSIBILITY OF SUCH DAMAGES. THE WARRANTIES SET FORTH HEREIN SUPERCEDE ALL OTHER WARRANTIES, EXPRESS, IMPLIED, STATUTORY OR OTHERWISE, INCLUDING, WITHOUT LIMITATION, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, AND THOSE ARISING FROM COURSE OF DEALING, USAGE OR TRADE PRACTICE. IN THE CASE WHERE ANY APPLICABLE LAW IMPOSES WARRANTIES, CONDITIONS OR OBLIGATIONS THAT CANNOT BE EXCLUDED OR MODIFIED, THIS PARAGRAPH SHALL APPLY TO THE GREATEST EXTENT PERMITTED BY SUCH LAW.

This Limited Warranty is made solely for the benefit of the original purchaser of the Product from NOCO or an NOCO-approved reseller or distributor and is not assignable or transferable. To assert a warranty claim, the purchaser must: (1) request and obtain a return merchandise authorization ("RMA") number and return location information (the "Return Location") from NOCO Support by emailing support@no.co or calling 1.800.456.6626; and (2) send the Product, including the RMA number, receipt or a warranty fee (fee only required if receipt is not provided) of 45% of the MSRP of the defective Product (the "Warranty Fee") [RMA will include the applicable Warranty Fee amount] to the Return Location. DO NOT SEND PRODUCT WITHOUT FIRST OBTAINING AN RMA FROM NOCO SUPPORT.

THE ORIGINAL PURCHASER IS RESPONSIBLE FOR (AND MUST PREPAY) ALL PACKAGING AND TRANSPORTATION COSTS TO SHIP PRODUCTS FOR WARRANTY SERVICE.

NOTWITHSTANDING THE FOREGOING, THIS LIMITED WARRANTY IS VOID AND DOES NOT APPLY TO PRODUCTS THAT: (a) are misused, mishandled, subjected to abuse or careless handling, accident, improperly stored, or operated under conditions of extreme voltage, temperature, shock, or vibration beyond NOCO's recommendations for safe and effective use; (b) improperly installed, operated or maintained; (c) are/have been modified without NOCO's express written consent; (d) have been disassembled, altered or repaired by anyone other than NOCO; (e) defects are reported after the Warranty Period.

THIS LIMITED WARRANTY DOES NOT COVER: (1) normal wear and tear; (2) cosmetic damage that does not affect functionality; or (3) Products where the NOCO serial number is missing, altered, or defaced.

You can register your NOCO product online at: no.co/register. If you have any questions regarding your warranty or product, contact NOCO Support (email and phone number above) or write to: The NOCO Company, 30339 Diamond Parkway, #102, Glenwillow, OH 44139 USA.

GB70.010919A

Warning

This content is compiled from multiple sources and is provided for reference purposes only. It may not be complete or fully applicable to all situations. If you are unable to resolve your issue, please contact the product manufacturer or an authorized service provider for official support.

Document generated by [ManualsFile](#)

