


Wireless Audio Adapter




MODEL: GT83

Please read this manual carefully before use

Product Parameters

Model: GT83	Transmission range: AUX
Audio decoding: SBC	Material: <10m
Product input: 5V/1A	Supported Protocols: ABS
Supported Protocols: A2DP, AVCTP, AVDTP, AVRCP, HFP, SPP	

Function Key Description



1

Pairing Operation

TX Mode

- First, insert the adapter into the headphone jack of the entertainment device you need to connect, or use the TYPE-C interface to connect your phone or tablet as the audio input;
- Push the mode button to TX, the red TX indicator light on the product will light up, and headphones 1 and 2 will flash;
- Open the wireless device that needs to be paired and adjust it to wireless pairing mode;
- The product will automatically search for nearby wireless devices to connect to. After successful connection, earphone 1 will remain on. Then, double-click the phone button to search for a second wireless device to connect to, and earphone 2 will remain on after successful connection.

(The first connection may take a few seconds, and it will automatically connect the next time the connection is successful)

- Mode switching: Long press the phone button to switch between TF card/AUX/PC playback modes.

Note:

After completing wireless pairing, press and hold the R key for 5 seconds to reset and search again;


If pairing fails, you can turn off the power and restart the wireless adapter and wireless earphones/speakers, repeat the above steps, and then try several times;

If you are using this product on a TV, please confirm which RCA port is the audio output port. The device needs to be connected to an RCA or 3.5mm audio output port, not an audio input port.

2

RX Mode

- Firstly, insert the adapter into the AUX-IN port of the speaker;
- Push the mode button to RX, the blue indicator light on the product will light up, and headphones 1 and 2 will flash;
- When the adapter is waiting for pairing, open the wireless settings of the phone, search for "GT83", and select pairing;
- After the first phone is successfully connected, earphone 1 stays on. When searching for "GT83" on the second phone and successfully connecting, earphone 2 stays on. At this point, you can use the adapter to play music wirelessly;
- Your phone was successfully paired for the first time and will automatically reconnect to your phone the next time it is turned on;
- Private call: When a call is answered and you want to switch back to a mobile call, long press the phone button to switch back to a mobile call;
- Wireless disconnection and reconnection: When the device is connected to the phone, double-click the phone button to disconnect the current connection, and double-click again to reconnect to the previous phone device;
- Mode switching: Long press the phone button to switch between TF card/BT playback modes.



3

Common Operation Instructions

1. Power ON/OFF



2. Definition Of Music Status Function



4

3. Definition Of Call Status Function



Safety Guidelines

- Please follow the instructions in this manual and do not disassemble or modify the device for any reason, otherwise it may cause the adapter to malfunction or burn out;
- Do not immerse the product in any liquid or rinse the product with water;
- Please use a charging cable that meets national/regional safety standards to charge the adapter, otherwise it may cause damage to the adapter battery or pose a danger;
- Please use and store this product in a room temperature environment, and do not place the device in an environment with too low or too high a temperature;
- Do not use the equipment during thunderstorm weather, as thunderstorms can cause abnormal equipment operation, signal interruption, and other phenomena.

5

FCC Warning

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
 - Increase the separation between the equipment and receiver.
 - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
 - Consult the dealer or an experienced radio/TV technician for help.
- NOTE 2: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
- The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

说明书尺寸：55x75mm 正反双面折页