



Please read all instructions before using this product and keep this guide for future reference.


Please read all instructions before using this product and keep this guide for future reference.

- To protect your hearing, avoid listening at high volume levels for extended periods of time.
- Lower the speaker volume before starting audio playback.
- Use this product only as intended.
- Do not attempt to open, modify, or disassemble the speaker.
- This product contains a built-in rechargeable lithium-ion battery that is not replaceable.
- Dispose of the product according to your local regulations and recycling guidelines.
- Battery performance may decrease over time or in extreme temperatures.
- Fully charge the speaker before storing it for extended periods.
- Disconnect the charging cable once the speaker is fully charged.
- Wireless performance may be affected by obstacles, wireless interference, or distance from your device.
- Do not expose the speaker to excessive heat, direct sunlight, moisture, or freezing temperatures.
- Do not leave the speaker inside a hot vehicle for extended periods.
- Do not use or use the product near water or allow it to become wet.
- Clean only with a soft, dry cloth. Do not use harsh chemicals or abrasive cleaners.
- This product is not a toy. Keep out of reach of small children unless supervised.

Thank you for choosing the Monsterlino Special Edition MagFlux speaker, created exclusively for FIAT Topolino. Designed for everyday adventures, Monsterlino delivers powerful wireless sound in a compact magnetic speaker that easily attaches to compatible smartphones and magnetic surfaces. Enjoy music, calls, and customizable RGBIC lighting effects wherever you go. For an even bigger experience, pair two speakers together using True Wireless Stereo and Color Sync technology. Please read this guide before using your speaker to ensure the best performance and safe operation.

- Wireless audio streaming
- Compact magnetic portable speaker
- RGBIC multicolor lighting effects
- Built-in microphone for calls
- USB-C fast charging
- microSD card playback support
- True Wireless Stereo (TWS) pairing
- Color Sync lighting between two speakers
- Includes magnetic adapter rings and lanyards

- Charging Input: 5 V / 1 A
- Output: 5 W
- Battery Capacity: 500 mAh
- Charging Time: Approx. 2 Hours
- Playback Time: Up to 6.5 Hours (50% volume)
- USB Cable Length: 39.37 in / 1 meter
- MicroSD Card Support: Up to 32 GB



1. RGBIC Passive Bass Radiator
2. Speaker
3. Microphone
4. Volume Down / Previous Track
5. Multi-Function Power Button
6. Volume Up / Next Track
7. MicroSD Card Slot
8. USB-C Charging Port & LED Indicator
9. Lanyard Attachment Slot
10. Magnetic Attachment Surface
11. Lanyard
12. USB-C Charging Cable
13. Magnetic Adapter Ring (Not Shown)
14. Travel Pouch (Not Shown)

1. Remove accessories from the package.
2. Fully charge the speaker before first use.
3. Power on and pair the speaker wirelessly.
4. Attach and enjoy

NOTE: Some accessories are packed underneath the inner tray insert. Be sure to remove and check all packaging materials before discarding the packaging.

- USB-C Charging Cable
- Magnetic Adapter Rings
- Lanyards
- Travel Pouch
- User Manual

1. Connect the included USB-C cable to the speaker.
2. Connect the other end to a USB power source or compatible USB adapter (not included).
3. The LED indicator beside the USB-C port will illuminate red while charging.
4. The LED indicator will turn off once charging is complete.

NOTE: When the battery level drops below 5%, the speaker will announce "Low Battery."

1. Insert the thin loop of the lanyard through the speaker's lanyard slot.
2. Pull the larger end of the lanyard through the loop.
3. Tighten securely.

Monstertino features a built-in magnetic surface designed for quick and convenient attachment to compatible magnetic surfaces and devices.

1. The speaker can attach directly to compatible magnetic smartphones and magnetic phone cases.
2. For additional magnetic support, the included magnetic adapter ring can be applied to compatible surfaces or phone cases.
3. Using the Magnetic Adapter Ring
4. Clean the desired surface thoroughly before application.
5. Remove the protective film from the adhesive side of the adapter ring.
6. Carefully position the ring and press firmly into place.

NOTE: The magnetic adapter ring is designed for one-time application and should not be removed or repositioned after installation.

Always confirm the speaker is securely attached before use.

- Use only on clean, flat, compatible surfaces.
- The magnetic adapter ring is not intended for use with wireless charging.

If attached directly to a smartphone or phone case, remove the ring before using a wireless charger. Failure to do so may cause overheating or damage.

- Press and hold the Multi-Function Power Button to turn on the speaker.
- The speaker will power on and automatically enter wireless pairing mode.
- Audio prompts and indicator sounds may be heard during startup, pairing, and connection.
- Open your smartphone's wireless device settings
- Select "Monsterino" from the list of available devices.
- Once connected, you will hear a confirmation prompt.

To Disconnect : Disconnect the speaker through your smartphone's wireless settings.

If the speaker does not connect:

- Make sure the speaker is powered on and charged.
- Confirm wireless is enabled on your smartphone.
- Move the speaker closer to your device.
- Restart your smartphone and try again.

NOTE: You can also play audio directly from a MicroSD card (up to 32 GB, sold separately).

NOTE: You can also play audio directly from a MicroSD card (up to 32 GB, sold separately).

True Wireless Stereo (TWS) allows both Monsterlino speakers to play together for enhanced stereo sound and Color Sync technology.

True Wireless Stereo (TWS) allows both Monsterlino speakers to play together for enhanced stereo sound and Color Sync technology.

To Connect Two Speakers:

1. Power on both speakers.
2. Place the speakers next to each other.
3. Triple-press the Multi-Function Power Button on either speaker.
4. Wait for the confirmation tone indicating TWS pairing is complete.
5. Open your smartphone's wireless settings and connect to "Monsterlino."

Once connected, both speakers will play synchronized stereo audio and lighting effects.

After pairing is complete, the speakers can be separated during use.

To Exit TWS Mode: Triple-press the Multi-Function Power Button again on either speaker.

Your smartphone will remain connected to one speaker wirelessly

Power On/Off: Press and hold the Multi-Function Power Button.

Power On/Off: Press and hold the Multi-Function Power Button.

Change Accent Lighting: Double-press the Multi-Function Power Button to cycle through lighting modes:

- Rainbow Flow
- Ambient Fade
- Red Pulse
- Blue Pulse
- Green Pulse

You may hear a power-off prompt or sound effect.

- **Play/Pause:** Press the Multi-Function Power Button once.
- **Previous Track:** Double-press the volume Down button (-).
- **Next Track:** Double-press the volume Up button (+).
- **Decrease Volume:** Press the volume Down button (-).
- **Increase Volume:** Press the volume Up button (+).

The speaker must be connected to your smartphone wirelessly to make or receive calls.

- The speaker must be connected to your smartphone wirelessly to make or receive calls.
- Answer or End a Call: Press the Multi-Function Power Button once.
 - Reject a Call: Press and hold the Multi-Function power button for 2 seconds.

NOTE: You will hear an audio alert when receiving an incoming call.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference.
2. This device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.
- The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

