



BL500 TWS Bluetooth Earphone Instruction Manual




Thanks for your purchase and use for our goods!

for better experience, please read the instrument carefully.

Specification

model:	BL 500
chipset:	JL6973D
Bluetooth version:	5.1
combination name:	BL500
connection distance:	10M/33 inch
RF injection rate:	CLASS2 5dBm
music time:	4.5 hour
dial time:	4 hour
single earphone weight:	3.1g
earphone charging time:	1 hour
battery box charging time:	2 hour
battery box life:	12 hour
earphone rate:	Li-on battery 3.7V/25mAh
battery box rate:	Li-on battery 3.7V/230mAh
charging port:	Lightning
speaker diameter:	speaker diameter=Φ13mm
speaker impedance:	32Ω±15%
Acceptance sensitivity:	—90dBm



iPhone operation

- 1.open the hat, power on
- 2.put earphone into battery box to power off or auto off when 3 minutes no connection
- 3.left and right earphone inside the boss, close hat, auto combination after 15 to 30 seconds, immediate combination by pressing the box button till the red lights on
- 4.open the Bluetooth, iPhone will show window pop-up, combine it by the tips
- 5.press two times on left or right earphone part to answer
- 6.press two times to hang off
- 7.long press 1 seconds to refuse dialing
- 8.hands operation to cancel combination with mobile
- 9.power off automatically when its no connection for 3 minutes
- 10.music pause/play, press left or right earphone 2 times
- 11.switch to last song: press left earphone 3 times
- 12.switch to next song: press right earphone 3 times
- 13.choose Bluetooth connection setup, press 2 seconds to activate SIRI
- 14.charging: orange lights on for 8 seconds then off
- 15.in-ear detection: put earphone out of ear and music pause, put it in eara, then music play automatically
- 16.wireless charge: put battery box in wireless charger center, auto detection and charging, red lights on

Android operating system mobile phone

- 1.open the hat, power on
- 2.put earphone into battery box to power off or auto off when 5 minutes no connection
- 3.left and right earphone inside the boss, close hat, auto combination after 15 to 30 seconds, immediate combination by pressing the box button till the red lights on
- 4.open the Bluetooth, search device"BL500", hands operation at first time.
- 5.press two times on left or right earphone part to answer
- 6.press two times to hang off
- 7.long press 1 seconds to refuse dialing
- 8.hands operation to cancel combination with mobile
- 9.power off automatically when its no connection for 3 minutes
- 10.music pause/play, press left or right earphone 2 times
- 11.switch to last song: press left earphone 3 times
- 12.switch to next song: press right earphone 3 times
- 13.charging: orange lights on for 8 seconds then off
- 14.in-ear detection: put earphone out of ear and music pause, put it in eara, then music play automatically
- 15.wireless charge: put battery box in wireless charger center, auto detection and charging, red lights on
- 16.tips: for the compatibility problem of Android system Bluetooth parts, few functions above is not available in some model



Warranty Card

Purchase date:	Warranty time:
Name:	Tel:
Email:	
Address:	
Warranty range:	
Warranty date:	

If the damage reason like below,sorry for no warranty service

- 1.the warranty effective period is over;
- 2.improper use to cause surface damage;
- 3.outside package and gift damage;
- 4.ignore the construction,wrong use and refit to cause damage.

Shenzhen Be-Fund Technology Co., Ltd.
Add: Room 2305 Jia'anda Building, 110 Huafan Road,
Dalang Street, Longhua District, Shenzhen, Guangdong, China
Web: szfoneng.com
Tel: 0755-36947220

