

## **Overview**

The CONAMBO JBT100 is a single-ear, on-ear Bluetooth headset designed for hands-free communication. It features dual-microphone noise cancellation, a long battery life, and is built for durability in active environments such as trucking, field service, and office work.



# Features and Specifications

## Key Features

- **Dual Microphone Noise Cancellation:** Utilizes ENC (Environmental Noise Cancellation) and CVC 8.0 technology to suppress up to 96% of background noise.
- **Extended Battery Life:** Up to 35 hours of talk time or 60 hours of music playback on a single charge (approx. 3.5 hours charging time).
- **Bluetooth 5.1:** Provides improved connectivity and a wireless range of up to 39 feet (12 meters). Supports multi-point connection for two devices simultaneously.
- **Durable Design:** IP54 rated for protection against dust and moisture.
- **Comfortable Fit:** Adjustable shape-memory headband and plush protein leather earcup.
- **Integrated Controls:** Features a multi-function button and a dedicated mute button.

## Technical Specifications

- **Model Name:** CNB100
- **Bluetooth Version:** 5.1
- **Battery Capacity:** 400mAh Lithium Polymer
- **Charging Port:** USB Type-C
- **Impedance:** 32 Ohms
- **Weight:** 0.33 kg (11.7 oz)
- **Water Resistance:** IP54 (Splash and dust resistant)
- **Included Components:** Charging cable.

## Use Guide

### Parts and Controls

The headset features the following main controls:

- **Multi-Function Button (Blue):** Used for power, pairing, answering/ending calls, and media playback control.
- **Mute Button:** Dedicated button to mute the microphone during a call.
- **USB Type-C Charging Port:** Located on the earcup for connecting the included charging cable.
- **Microphones:** Dual microphones for noise cancellation are integrated into the boom.
- **Status Indicator Light:** A blue LED that displays pairing and charging status.



## Charging the Headset

1. Connect the provided USB Type-C cable to the charging port on the headset.
2. Connect the other end of the cable to a USB power adapter or computer port.
3. The indicator light will show the charging status. A full charge takes approximately 3.5 hours.

## Pairing with a Device

1. Ensure the headset is charged.
2. Press and hold the **Multi-Function Button** for about 5 seconds until the blue indicator light flashes rapidly (pairing mode).
3. On your smartphone, tablet, or computer, enable Bluetooth and search for available devices.
4. Select "**JBT100**" from the list of discovered devices.
5. If prompted, confirm the pairing. A voice prompt or solid blue light indicates a successful connection.

## Basic Operations

- **Answer a Call:** Press the **Multi-Function Button** once.
- **End a Call:** Press the **Multi-Function Button** once.
- **Reject a Call:** Press and hold the **Multi-Function Button** for about 2 seconds.
- **Redial Last Number:** Double-press the **Multi-Function Button** when not on a call.
- **Mute/Unmute Microphone:** Press the dedicated **Mute Button** during a call. (Note: Mute function is currently supported on mobile phones only).
- **Activate Voice Assistant (Siri/Google Assistant):** Press and hold the **Mute Button** for about 2 seconds when connected.



## Wearing and Adjusting

Extend the headband to fit over your head. The shape-memory metal band will conform to your head size. Position the earcup over your ear, ensuring the microphone boom is angled towards your mouth for optimal noise cancellation performance.

## Care and Maintenance

- Clean the earcups and headband with a soft, dry cloth. Do not use liquids or abrasive cleaners.
- Store the headset in a dry place when not in use.
- The headset is rated IP54 for dust and water resistance. It is protected against splashes from any direction but is not submersible. Do not charge the headset if it is wet.
- Use only the provided or certified USB Type-C cable for charging.

## Troubleshooting

- **Headset won't turn on:** Charge the headset fully.

### **Cannot pair with device:**

- Ensure the headset is in pairing mode (blue light flashing rapidly).
  - Move the headset and device closer together during pairing.
  - Reset the headset (see below) and try pairing again.
- **Poor call quality or background noise:** Ensure the microphone boom is positioned close to your mouth. The noise cancellation is optimized for this position.
  - **Headset not connecting to a previously paired device:** Turn the device's Bluetooth off and on again, or delete "JBT100" from your device's Bluetooth list and re-pair.

## Resetting the Headset

To clear all pairing records and restore factory settings:

1. Ensure the headset is on.
2. Press and hold the **Multi-Function Button** for 3 seconds.
3. Release the button when you see the blue indicator light flash rapidly three times. The reset is complete.

## Warranty and Support

For warranty information about this product, please [click here](#).

### Warning

This content is compiled from multiple sources and is provided for reference purposes only. It may not be complete or fully applicable to all situations. If you are unable to resolve your issue, please contact the product manufacturer or an authorized service provider for official support.