

## 1. Overview

The Conambo Trucker Bluetooth Headset V5.0 is a wireless on-ear headset designed for professional and personal communication. It features Bluetooth 5.0 connectivity, a noise-canceling microphone, and includes a USB dongle for use with devices that lack built-in Bluetooth. It is intended for use by truck drivers, in call centers, for remote work, online conferences, and with computers or mobile phones.



Key design elements include a retractable headband, a 300° rotatable microphone boom, and on-ear earpads.

## 2. What's in the Box

- Bluetooth Headset
- USB Adapter (Dongle)
- Charging Cable (Micro-USB)

## 3. Features and Specifications

### 3.1 Connectivity

- **Bluetooth Version:** 5.0
- **Wireless Range:** Up to 10 meters (approx. 30 feet).
- **USB Dongle:** Allows connection to PCs and laptops without built-in Bluetooth.
- **Compatible Devices:** Cell phones, laptops, desktop PCs.

### 3.2 Audio & Microphone

- **Noise Cancellation:** Features noise reduction technology for the microphone to minimize background noise.
- **Ear Placement:** On-Ear.
- **Noise Control:** Passive Noise Cancellation.
- **Microphone:** Boom microphone is rotatable 300° and can be worn on the left or right ear. The mic boom is bendable for optimal positioning.



### 3.3 Battery

- **Talk Time:** Up to 16 hours.
- **Standby Time:** Up to 160 hours.

- **Charging Time:** Approximately 3.5 hours.
- **Charging Port:** Standard Micro-USB.

### 3.4 Physical Design

- **Weight:** Approximately 2.8 ounces (headset only).
- **Headband:** Retractable to fit different head sizes.
- **Color:** Black.
- **Material:** Plastic.



## 4. Use Guide

### 4.1 Charging the Headset

1. Connect the provided Micro-USB cable to the charging port on the headset.
2. Connect the other end of the cable to a USB power source (e.g., computer USB port or USB wall adapter).
3. The headset will charge. A full charge takes approximately 3.5 hours.

### 4.2 Power On / Off & Pairing

**Controls:** The headset has a Multifunction (MF) button and separate Volume Up/Down buttons.

- **To Power On:** Press and hold the MF button until the indicator light turns on (or you hear a power-on prompt).
- **To Enter Pairing Mode:** Ensure the headset is powered off. Then press and hold the MF button until the indicator light flashes rapidly (typically red and blue alternating). The headset is now discoverable by your Bluetooth device.

- **To Power Off:** Press and hold the MF button until the indicator light turns off (or you hear a power-off prompt).

### 4.3 Connecting to a Device

#### Via Bluetooth (Phones, Tablets, Bluetooth-enabled PCs):

1. Enable Bluetooth on your device.
2. On your device, search for available Bluetooth devices.
3. Select "JBT800" or a similar name from the list.
4. If prompted, confirm pairing. The headset indicator will typically become solid or slow-blinking once connected.

#### Via USB Dongle (PCs/Laptops without Bluetooth):

1. Insert the provided USB dongle into an available USB port on your computer.
2. The operating system should automatically install necessary drivers.
3. Power on the headset. It should automatically connect to the dongle.
4. Select the headset as your computer's audio input and output device in your system sound settings.

### 4.4 Wearing the Headset

1. Adjust the retractable headband by pulling the earcups apart to fit your head size comfortably.
2. Rotate the microphone boom to the side of your face (left or right ear) as preferred.
3. Bend the microphone boom so the mic is positioned approximately 1-2 inches from the corner of your mouth for optimal voice pickup.

### 4.5 During a Call (Phone Functions)

- **Answer a Call:** Press the MF button once.
- **End a Call:** Press the MF button once.
- **Reject a Call:** Press and hold the MF button for about 2 seconds.
- **Adjust Volume:** Press the Volume Up (+) or Volume Down (-) buttons.
- **Redial Last Number (Functionality may vary):** Quickly press the MF button twice when not on a call.

*Note: Call control functions (answer/end/reject) are specified as working with phones. Functionality with computers/softphones may depend on the software being used.*

## 5. Product Information

<b>Model Name</b>	JBT800-Dongle
<b>Connectivity Technology</b>	Wireless
<b>Wireless Communication Technology</b>	Bluetooth
<b>Headphones Jack</b>	USB (via dongle)
<b>Form Factor</b>	On Ear
<b>Control Type</b>	Button (Volume Control, Multifunction)
<b>Battery Type</b>	1 Lithium Polymer battery (included)
<b>Item Weight</b>	5.3 ounces (Package Weight)
<b>Manufacturer</b>	Conambo
<b>ASIN</b>	B0DCYXTBMD

## 6. Compatibility

This headset is compatible with devices that support Bluetooth hands-free profile (HFP) or the USB audio class via the included dongle. This typically includes:

- Cellular Phones (Smartphones)
- Tablet Computers
- Laptop and Desktop Computers (with or without built-in Bluetooth)
- MP3 Players with Bluetooth

## 7. Warranty & Support

**Product Warranty:** For warranty information about this product, please [click here](#).

### Warning

This content is compiled from multiple sources and is provided for reference purposes only. It may not be complete or fully applicable to all situations. If you are unable to resolve your issue, please contact the product manufacturer or an authorized service provider for official support.

