

Application

Power cord connection

Tube Installation

Fixture Installation

Rotate the lamp holder

Suspension Installation

Suspension Installation

Instructions:

1. Remove fixture from box along with all accessories
2. When inserting lamps, be gentle and rotate the lamps with both hands from the ends.

These lamps are fragile!

3. Insert lamps into the fixture (Make sure on/off switches are in the off position)
5. Plug in the fixture to an outlet
6. Turn switch(s) to the on position
7. The fixture is now ready to be hung.
8. Attach the cable hangers and mount the fixture to the mounting point on the ceiling.
9. This unit has a daisy chain feature - up to three (3) fixtures per chain

Caution:

1. For indoor use only.
2. Commercial T5 is to be installed by licensed electrician only.
3. Before servicing the reflector, make sure the on/off switches are in the off position.
4. To prevent fire and electrocution, do not alter, modify, or disassemble the fixture.
5. When the product exhibits unusual behavior, such as flickering, dimming, or pulsing.
6. Do not cover the fixture in insulation or fabric materials.
7. Do not install the fixture on an unstable mount or surface.

Specification:

1. AC Voltage range: 110 to 277 V
2. Frequency: 50Hz
3. Lamp wattage (per tube): 54W
4. Number of lamps: 8

5. Length of tube: 4 ft.

Warning

This content is compiled from multiple sources and is provided for reference purposes only. It may not be complete or fully applicable to all situations. If you are unable to resolve your issue, please contact the product manufacturer or an authorized service provider for official support.

Document generated by [ManualsFile](#)

