

FEATURES

1. Ultra-large magnetic circuit high-sensitivity speaker with high penetrating power, low-frequency shock and perfect medium-/high-frequency representation.
2. The latest decoding chips supporting stably playback of MP3 in up to 32GB U disk/SD card.
3. FM radio reception-high-quality digital radio with automatic channel search and storage of up to 60 channels.
4. 3.5mm AUX audio input for each connection to a wide range of sound sources.
5. Built-in high-capacity battery for consecutive playback of up to 2 hours.
6. Connect the microphone, adjustable reverberation, voice and Karaoke function to present outstanding performance.
7. Battery with built-in recharging protection to present a long and stable service life.
8. Built-in low battery and full recharging indication. Human-oriented use.
9. With belt/handle design for best choice of mobile speaker.
10. Outputs to earphone or external sound sources.
11. Record your favorite FM radio station or other AUX sound source to enjoy the music wherever you are.
12. Microphone input recording to act as your personal business assistant.
13. With Wireless BT function.

RECORDING

Recording in AUX Mode:

Connect a storage device (USB/SD card) and press Mode key to enter AUX mode. Short press Record key to start recording for a time depending on the storage capacity. The signal should be strong during recording.

Recording in FM Receiving Mode:

Connect a storage device (USB/SD card) and press Mode key to enter FM mode. Select your favorite radio station and short press record key to start recording for a time depending on the storage capacity. During recording, keep the device in a proper location with strong radio signal to ensure optimized recording performance.

Recording via External Microphone:

Connect a storage device (USB/SD card) and short press RECORD key to start recording for a time depending on the storage capacity. During recording, turn the “-ECHO+” knob to the


minimum. It is best that the microphone should have a proper distance away from the speaker to prevent any feedback.


NOTE: This product starts recording from the time as displayed on the LED screen.




WIRELESS BT PAIRING OPERATION

1. ON/OFF: switch the power to ON, press the key "MODE" to enter the Wireless BT mode, the display screen will show "BLUE" indicating Wireless BT mode is active.
2. Make sure the Wireless BT function of the Mobile device is active and begin searching. Connect to mobile device when "PyleUSA" shows. Mobile device connections do not need password, however if prompted, input "0000" to go on pairing. After a successful pairing, the speaker will send out a voice prompt indicating it has successfully been paired with the mobile device.
3. Play the music from your mobile device directly and enjoy.

FUNCTIONAL OPERATIONS AND FEATURES









1. LED Screen
2. Master Volume: In MP3/FM/AUX mode, use it to regulate volume output from the speaker.
3. SD Port: Read audio files in MP3 format in SD card in capacity up to 32G (FAT32).
4. USB Port: Read audio files in MP3 format in USB storage device in capacity up to 32G (FAT32).
5.  : In USB/Micro SD card reading mode, short press to go to the previous track, or press and hold to switch to the previous folder. In FM receiving status, short press it to select the previous channel after a full station search has been executed.


6.  : In USB/SD card reading mode, short press it to play/pause, or press and hold to select one of four playback sequencing modes (All - play all tracks in sequence; ONE - repeat one track). In FM receiving status, press and hold to execute a full search (it is recommended to execute at least one full search before using radio receiving function. All founded stations will be saved even in power-off). In AUX input / FM radio status, short press it to toggle between mute and normal volume.
7.  : In USB/SD card reading mode, short press it to go to the next track. In FM receiving status, short press it to select the next channel after a full station search has been executed.
8. **Mode/SHIFT:** Short press it to toggle between USB/SD and FM receiving modes. Press and hold to toggle between recording folder and MP3 folder.
9. **Recording/DEL:** Short press it to enable recording (USB/SD storage device need be connected first).
During recording, reverberation should be tuned to the minimum. Press and hold to delete a recording file. Recording in AUX or FM mode is available.
10. **EAR MIC:** Headphone/MIC Port
11. **EQ:** Environment Switching: In USB/SD reading status, short press it to select an environment mode (from Square, Meeting, Home, Hall and Personal).
12. **Microphone input:** Microphone input jack
13. **LINE IN:** External sound source input port (plug-and-play).
14. **Reverberation:** Microphone reverberation regulating knob.
15. **Microphone volume:** Microphone volume regulating knob.
16. **DC 12V recharging:** DC 12V recharging port.
17. **LED Power:** The ON/OFF button of light
18.  : In MP3 mode, Press and hold to toggle between 6 kinds of flash modes/ the flash light switch.
In FM/MIC IN mode, press and hold to control the flashlight switch.
19. **Power switch:** “ - ” - ON; “ **O** ” - OFF.
20. **TREBLE:** The control knob of treble.
21. **BASS:** The control knob of bass
22. **LED MODE 1:** First lighting mode
23. **LED MODE 2:** Second Lighting mode
24. **IR:** Infrared remote receiver module

NOTE: Please charge the speaker when the unit is off or lower the volume to avoid distortion.

REMOTE INSTRUCTIONS



1. **Power Button:** Short press to enter standby mode; short press it again to resume.
If no device is connected, the system goes to “-NO-”.
2.  : Functions as “” on the master device.
3.  : Functions as “” on the master device.
4.  : Functions as “” on the master device.
5. **Mode:** Functions as “Mode” on the master device.
6. **V + / V- Keys:** In USB/SDF/FM/AUX mode, press them to volume up/down.
7. **Numeric Keys 0~9:** In USB/SD card reading status, to play Track 12, just input numbers “1” and “2”, and in 2 seconds the system will go to Track 12 and start playback. Any input of number larger than number of the total available tracks is invalid. In FM status, to listen to channel 107.5MHZ, just input “1075”.
8. **Environment Key:** In USB/SD card reading status, short press it to toggle among Square, Meeting, Home, Hall and Personal modes.
9. **Sequencing Key:** In USB/SD card reading status, short press it to toggle among four playback sequencing modes (All - play all tracks in sequence; RAND - play in random; ONE - repeat one track; FOL - repeat all tracks in a folder).

10.  : In USB/SD/FM/AUX mode, short press it to mute the device.

11. **100+**: Number selection key - in MP3 mode (USB/SD card), short press it to add “**100**” to current track number.

What's in the Box:

- Portable PA Speaker
- Wired Handheld Microphone
- Headset Microphone
- Lavalier Microphone
- Audio (Aux) Connection Cable
- Power Adaptor
- Remote Control

Audio Recording:

- It's Easy: One Button Recording Activation
- Record Audio as Streamed through the Speaker System
- Ability to Record Vocals via Microphone
- Records to USB Flash or Micro SD Card
- Audio File Type Created: .MP3
- Easy Transfer to PC & Mac

Features:

- Karaoke & Music Streaming Speaker System
- Compact, Portable & Powerful
- Bluetooth Wireless Audio Streaming
- Built-in Rechargeable Battery
- Flashing DJ Party Lights
- FM Radio with Digital LCD Display
- USB Flash & Micro SD Memory Card Readers
- MP3 Digital Audio File Compatibility
- Includes Handheld Wireless Microphone
- Audio File Recording Function
- Headphone Jack
- Aux (3.5mm) Input
- Microphone Input

- Connect & Stream From External Devices
- Full Range Stereo Sound Reproduction
- Impressive Bass Response
- Convenient Carry Handle & Rolling Wheels
- Rugged & Heavy Duty Design
- Top Panel Button Control Center

Wireless BT Connectivity:

- Built-in BT for Wireless Streaming
- Works with All of Your Favorite Devices (Smartphone, Tablet, Laptop, Computer, etc.)
- Wireless BT Network Name: 'PyleUSA'
- Wireless BT Password: '0000'
- Wireless BT Wireless Range: 65'+ Ft.
- Wireless BT Version: 2.0

Technical Specs:

- Power Output: 550 Watt MAX
- Sound System: 8" Subwoofer
- Wired Microphone Cable Length: 16.5' ft.
- Battery: Lead Acid, 3500mah 11.1V
- Impedance: 4 Ohm
- Sound Distortion: <1.0%
- S/N Ratio: ≥85dB
- Max USB/SD Memory Card Support: 32GB
- Power Supply: 100/240V (DC 12V Power Adapter)

Warning

This content is compiled from multiple sources and is provided for reference purposes only. It may not be complete or fully applicable to all situations. If you are unable to resolve your issue, please contact the product manufacturer or an authorized service provider for official support.